







15NDL76

LF Drivers - 15.0 Inches

1000 W continuous program power capacity 76 mm (3 in) copper voice coil 40 - 2000 Hz response 99.5 dB sensitivity Neodymium magnet allows a very light yet powerful motor assembly Ventilated voice coil gap for reduced power compression

Specifications

Nominal diameter	380 mm (15.0 in)	
Nominal impedance	8 Ω	
Minimum impedance	6.7 Ω	
Nominal power handling ¹	500 W	
Continuous power handling ²	1000 W	
Sensitivity (1W/1m) ³	99.0 dB	
Frequency range	40 - 2000 Hz	
Voice coil diameter	76 mm (3.0 in)	
Winding material	Copper	
Former material	Glass Fibre	
Winding depth	18 mm (0.68 in)	
Magnetic gap depth	11 mm (0.4 in)	
Flux density	1.25 T	
Design		

Design Surround shape Triple Roll Cone shape Exponential Neodymium Magnet material Inside Slug

Design

Single

ft³)

Parameters⁴

47 Hz

37 Hz

5.3 Ω

0.24

4.5

0.22

ft³)

195.0 dm³ (6.8

855.0 cm²

(132.5 in²)

4.1 %

7.0 mm

9.0 mm

22.5 Txm

96 g

Straight Pole

WP Waterproof Front Side

100.0 dm³ (3.53

Spider

Pole design

Woofer cone

Recommended enclosure

Recommended

treatment

tuning

Fs

Re

Qes

Qms

Qts

Vas

Sd

ηo

Xmax

Xvar

Mms

BI

Parameters

Le	1.5 mH
EBP	154 Hz

Mounting And Shipping Info

Overall diameter	393 mm (15.5 in)
Bolt circle diameter	374 mm (14.7 in)
Baffle cutout diameter	354.0 mm (13.9 in)
Depth	171 mm (6.7 in)
Flange and gasket thickness	16 mm (0.62 in)
Air volume occupied by driver	3.5 dm ³ (0.12 ft ³)
Net weight	4.6 kg (10.1 lb)
Shipping units	1
Shipping weight	5.9 kg (13.0 lb)
Shipping box	420x420x200 mm (16.5x16.5x7.9 in)

Service Kit

RCK15NDL768

2 hours test made with continuous pink noise signal (6 dB crest factor) within the range Fs-10Fs. Power calculated on rated minimum impedance. Loudspeaker in free air.

2. Power on Continuous Program is defined as 3 dB greater than the Nominal rating.

3. Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.

4. Thiele-Small parameters are measured after a high level 20 Hz sine wave preconditioning test.

B&C SPEAKERS

